

04/2006 06-04-02-1 FT





Remarks


A mechanical stop must protect the load cell against "static" overloads. The ajustment of this stop must leave a gap at least equal to the load cell's deflection under full load. The load cell must also be protected by shock absorbers against shocks, dynamic overloads or vibrations.

Mechanical installation

On metal foot

The force to be measured must be applied on the axis of the load point, without gap, inclination or torsion.






Right mounting


Wrong mounting

On a metal supporting structure

The load cell must be fitted on the axis of the structure.








Wrong mounting

The supporting structure must be so stiff that it does not bend under the weight of the load. Reinforcement of the structure may in some cases be necessary.



Application

- Weighing silos, hoppers, tanks.



Presentation

General information

The CMI load cell consists of a stainless steel body and is hermetically sealed by laser welded stainless steel cups.

It has been designed for used in industrial environments with an aggressive atmosphere, such as the chemical industry. CMI load cells have a test certificate for 3 000d. Meating the IP 68 standard, CMI load cells are compact and available in four capacities: 500, 1 000, 2 000

Special mounting parts to adapt the load cell to its mechanical environment are available as an option.

Description

The working principle of the CMI load cell is to measure the deformation of a beam subjected to shear stress. The strain gauges are arranged to form a Wheatstone bridge, converting the mechanical force exerted on the load cell into an electrical signal.

Conformity

Test certificate issued by a notified body in accordance with OIML recommendation R60.




Option

Ex version for use in explosive and according to new directive 94/09/ CE. EEx ia IIC T6.

CE type certificate Nr: LCIE 02 ATEX 6083 X




Wiring



Technical data

Dimensions



СМІ		500	1000	2000	5000
Α	mm	59	56	53.5	104
В	mm	30	30	30	44
С	mm	10	10	10	15
D	mm	14.5	13.4	15.3	21.4
Е	mm	20	20	20	32
F	mm	14	14	14	22

СМІ		500	1000	2000	5000
G	mm	130	130	130	192
Н	mm	17.4	17.4	16.4	38.6
- 1	mm	25.4	25.4	25.4	38.1
J	mm	76.2	76.2	76.2	95.3
K	mm	30	30	30	40
1	mm	12.3	12.3	12.3	20.5

Metrological data

CMI		500	1 000	2 000	5 000	
Nominal load	Emax	500	1 000	2 000	5 000	kg
Minimum load	Emin	5	5	20	40	kg
Minimum division	v min	50	100	200	500	g
Max. number of divisions	n max	3 000	3 000	3 000	3 000	

Mechanical data

CMI	500	1 000	2 000	5 000	
Maximum load	750	1 500	3 000	7 500	kg
Breaking load	1 000	2 000	4 000	10 000	kg
Deflexion under nominal load	0.3	0.6	1.2	1.1	mm
Fixation screws (not supplied)	M12x45*	M12x45*	M12x45*	M20x65**	
Tightening torque (min - max)	3.5/4	3.5/4	3.5/4	7/9	daN.m

- * Minimum length = 45 mm ** Minimum length = 65 mm

Electrical characteristics

Maximum excitation voltage ac or dc	12 V
Input impedance	420 Ω ± 10%
Output impedance	351 Ω ± 2 Ω
insulation resistance	$>$ 5 000 M Ω
Sensitivity	$2 \text{ mV/V} \pm 0.1\%$
Non-repeatability	< 0.005%
Temperature effect on sensitivity	< 0.0009 % / °C
Temperature effect on zero balance	< 0.0014 % / °C
Shielded cable, in black PVC jacket	
• O.D	4.8 mm
Length CMI 500, 1000, 2000 CMI 5000	
Max. bending radius	20 mm


Environment

Temperature range	
Recommended	10 °C / + 40 °C
Without alteration	20 °C / + 60 °C
Storage	25 °C / + 80 °C
 Protection according to EN 60-529 	




Options*


Hopper mounting - Shock absorber



Hopper mounting - Ball bearing and stop



Traction mounting with rings



Standard marking



Ex version marking



^{*} Arrangement may vary with each model.



Illustrations are not contractual. Precia-Molen reserves the right to modify at any time, without prior notice, the information contained in this leaflet.

Offices and Factory P.O. Box 106 - F 07000 Privas - France 33 (0) 475 664 600 Tel. 33 (0) 475 658 330 E-MAIL webmaster@preciamolen.com

RCS: 386 620 165 RCS Aubenas

